# **PRO-HC**

Use this rugged, professional-grade Wi-Fi controller for residential and light commercial applications.

## **KEY BENEFITS**

- Number of stations:
- 6, 12, or 24 (fixed models)
- Standard programming option allows for 6 independent irrigation programs and 6 start times per program
- Advanced programming option provides station-based programming with up to 6 total start times available
- 2 sensor inputs available for use with any Clik sensor and HC Flow Meter
- $1\,\text{P/MV}$  output for pump start relay and master value activation
- Wi-Fi enabled for quick connection to Hydrawise software
- 7 cm full-colour touchscreen display for simple programming at the control panel
- Built-in milliamp sensor for wire fault detection and alerts

### **OPERATING SPECIFICATIONS**

- Transformer input: 120 VAC or 230 VAC
- Transformer output (24 VAC): 1 A
- Station output (24 VAC): 0.56 A
- P/MV output (24 VAC): 0.28 A
- 2.4 GHz (only) Wi-Fi router compatible, 802.11 b/g/n 20 MHz
- Supported security protocols: WPA/WPA2 Personal (only) TLS, SSL
- Approvals: IP44 (outdoor), UL, cUL, FCC, CE, RCM, ISED
- Warranty period: 2 years

#### **USER-INSTALLED OPTIONS**

• Wireless HC Flow Meter option permits wireless flow monitoring for Hydrawise enabled systems









#### Pro-HC

(plastic outdoor) Height: 22.8 cm Width: 25 cm Depth: 10 cm

## Compatible with:



Sensor

low Meter

Rain-Clik Sensor



#### Smart WaterMark

Recognised as a responsible water-saving tool

HYDRAWISE CONTROLLERS

PRO-HC - SPECIFICATION BUILDER: ORDER 1 + 2 + 3 + 4						
1 Model	2	Transformer	3	Indoor/Outdoor	4	Options
PHC-6 = 6-station controller PHC-12 = 12-station controller PHC-24 = 24-station controller		= 120 VAC <mark>= 230 VAC</mark>	(in <b>i</b> =	<b>ank)</b> = Outdoor model ternal transformer) Indoor model ug-in transformer)	E = Eu no A = Au (ou int	ank) = No option = 230 VAC with ropean connections, plug = 230 VAC with stralian connections utdoor model has ernal transformer th plug)

Example:

PHC-2400 = 24-station, 120 VAC, outdoor plastic controller

